

Handheld Digital Multimeters

DMM150 * CMM150 * DMM157



CMM150/DMM150/DMM157.

- On the left is the DMM150 with optional CMM150 clamp; on the right is the DMM157.

[Features](#)

[> Specs](#)

[Ordering Information](#)

[Pricing Information](#)

[Request a Quote](#)

CHARACTERISTICS

DC Volts

Input Resistance: 10 megaohm paralleled by < 100 pF.

Overload Protection: 600 V AC/DC RMS.

AC Volts

Input Resistance: 10 megaohm paralleled by < 100 pF.

Overload Protection: 600 V AC RMS.

DC Current (DMM157 Only).

Overload Protection: 10 A range: 13 A (250 V) HBC 6 KA fuse; Other ranges: 1 A (250 V) HBC 6 KA fuse.

Burden Voltage: 2 A, 10 A ranges: 900 mV max; Other ranges: 600 mV max.

AC Current (DMM157 Only)

Overload Protection: 10 A range: 13 A (250 V) HBC 6 KA fuse; Other ranges: 1 A (250 V) HBC 6 KA fuse.

Burden Voltage: 2 A, 10 A ranges: 900 mV max; Other ranges: 600 mV max.

Resistance

Overload Protection: 600 V AC/DC rms.

Test Voltage (open circuit):

Low power Ohm: 0.45 V max

(DMM157 only);

High power Ohm: 0.9 V max.

Capacitance (DMM157 ONLY)

Accuracy: \pm (1.9% of rdg + 5 cts).


Input Protection: 600 V AC/DC rms.

Safety

UL1244, CSA231, EN61010-1.

Warranty

3 Years.

 [Top of Page](#)

[Features](#)

[> Specs](#)

[Ordering Information](#)

[Request a Quote](#)

Product manufactured in ISO 9001 registered facilities



49A-10733-3p481, 06/1997, 09/01/1999

 [Email this page](#)

 [URL for Favorites](#)

 [Printable page](#)

Tektronix Site

[Home](#) | [Products](#) | [Support](#) | [Sitemap](#) | [Search](#) | [Privacy Policy](#)

© [Copyright Tektronix, Inc.](#) | webmaster@tek.com