

Agilent N9355/6 Power Limiters

N9355/6B 10 MHz to 18 GHz power limiter
N9355/6C 10 MHz to 26.5 GHz power limiter
N9355F 10 MHz to 50 GHz power limiter



N9355/6 Key Specifications & Features

- Protect your investment from excess RF power, DC transients and ESD damage with Agilent's broadband power limiters
- Maximize your operating frequency range from 10 MHz to 50 GHz
- Minimize your measurement uncertainty and improve your measurement accuracy with superior RF performance
- Select from two limiting threshold models of 10 dBm or 25 dBm to meet your specific application needs



Agilent Technologies

The Agilent N9355/6 Series of high performance power limiters are designed for high volume manufacturers and R&D sectors in telecommunications, component test, and aerospace/defense industries. Agilent's power limiters provide the best broadband input protection from excess RF power, DC transients and ESD, for a variety of RF and microwave instruments and components, like spectrum analyzers, network analyzers, and amplifiers.

Agilent limiters also include a DC block integrated into both input and output ports that will block signals below 10 MHz and pass signals up to 50 GHz.



Protect your investment from excess RF power, DC transients and ESD damage with Agilent's broadband power limiters.

Specifications

Power limiter	N9355B	N9356B	N9355C	N9356C	N9355F
Frequency range	0.01 to 18 GHz	0.01 to 18 GHz	0.01 to 26.5 GHz	0.01 to 26.5 GHz	0.01 to 50 GHz
Frequency response					
Insertion loss	< 1.75 dB	< 1.75 dB	< 2 dB	< 2.25 dB	< 2.75 dB
Return loss ¹ (VSWR)	> 15 dB (1.43)	> 15 dB (1.43)	> 15 dB (1.43)	> 15 dB (1.43)	> 10 dB (1.92)
Impedance	50 Ω nominal	50 Ω nominal	50 Ω nominal	50 Ω nominal	50 Ω nominal
Max. input power	1W	6W	1W	4W	0.63W
Limiting threshold	10 dBm typical	25 dBm typical	10 dBm typical	25 dBm typical	10 dBm typical
Max. leakage power ²	24 dBm	27 dBm	24 dBm	27 dBm	24 dBm
Max. DC voltage					
@ 25 °C	30 V	30 V	30 V	30 V	30 V
@ 85 °C	16 V	16 V	16 V	16 V	16 V
Turn on time	< 100 ps				
Connectors	Type-N	Type-N	3.5 mm	3.5 mm	2.4 mm

1. Return loss specification at 10 M to 30 MHz is 8.5 dB (VSWR: 2.2).

2. At maximum continuous input power

Web Resource <http://www.agilent.com/find/mta>



www.agilent.com/find/open

Agilent Open simplifies the process of connecting and programming test systems to help engineers design, validate and manufacture electronic products. Agilent offers open connectivity for a broad range of system-ready instruments, open industry software, PC-standard I/O and global support, which are combined to more easily integrate test system development.



Agilent Direct

www.agilent.com/find/agilentdirect

Quickly choose and use your test equipment solutions with confidence.

www.agilent.com

For more information on Agilent Technologies' products, applications or services, please contact your local Agilent office.

Phone or Fax

United States:

(tel) 800 829 4444

(fax) 800 829 4433

Canada:

(tel) 877 894 4414

(fax) 800 746 4866

China:

(tel) 800 810 0189

(fax) 800 820 2816

Europe:

(tel) 31 20 547 2111

Japan:

(tel) (81) 426 56 7832

(fax) (81) 426 56 7840

Korea:

(tel) (080) 769 0800

(fax) (080) 769 0900

Latin America:

(tel) (305) 269 7500

Taiwan:

(tel) 0800 047 866

(fax) 0800 286 331

Other Asia Pacific

Countries:

(tel) (65) 6375 8100

(fax) (65) 6755 0042

Email: tm_ap@agilent.com

Contacts revised: 05/27/05

The complete list is available at:
www.agilent.com/find/contactus

Product specifications and descriptions in this document subject to change without notice.

© Agilent Technologies, Inc. 2005, 2006

Printed in USA, April 17, 2006

5989-3740EN



Agilent Technologies