



5300 Beethoven Street, Los Angeles, CA 90066
 TEL: (310)306-5556 • FAX: (310)821-7413
 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5274
0.7 - 3.0 GHz
120 WATTS
LINEAR POWER RF AMPLIFIER

**Solid State
 Broadband High
 Power RF Amplifier**

The 5274 is a 120 Watt broadband amplifier that covers the 0.7 – 3.0 GHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 5274 comes with an extended multiyear warranty.

	<u>Parameter</u>	<u>Specification @ 25° C</u>
<u>Electrical</u>		
1	Frequency Range	0.7 – 3.0 GHz
2	Saturated Output Power	120 Watts typical
3	Power Output @ 1dB Comp.	80 Watts Minimum
4	Small Signal Gain	+52 dB min
5	Small Signal Gain Flatness	± 3.0 dB max
6	IP ₃	+56 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-20 dBc typical @ 80 Watts
9	Spurious Signals	< -60 dBc typical @ 80 Watts
10	Input/Output Impedance	50 Ohms nominal
11	AC Input Power	1200 Watts max
12	AC Input	100 – 240 VAC, single phase
13	RF Input	+10 dBm max
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	A
<u>Mechanical</u>		
16	Dimensions	19" x 5.25" x 26"
17	Weight	48 lbs.
18	Connectors	Type-N
19	Grounding	Chassis
20	Cooling	Internal Forced Air
<u>Environmental</u>		
21	Operating Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport

Specifications subject to change without notice



FE MODEL SHOWN

ORDERING MODELS:

- ◇ RE Rear RF Connector model with Front Panel Controller Ethernet, IEEE-488 and RS232
- ◇ FE Front RF Connector model with Front Panel Controller Ethernet, IEEE-488 and RS232
- ◇ R Rear RF Connector model
- ◇ F Front RF Connector model



5300 Beethoven Street, Los Angeles, CA 90066
TEL: (310)306-5556 • FAX: (310)821-7413
WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5274 0.7 - 3.0 GHz 120 WATTS LINEAR POWER RF AMPLIFIER

FRONT PANEL CONTROLLER FEATURES

- ◇ Forward Power Monitoring (dBm or Watts)
- ◇ Reflected Power Monitoring (dBm or Watts)
- ◇ Gain Control (Dynamic range of 20 dB)
- ◇ Fault Status
- ◇ Full Protection Of any VSWR Condition, Open or Short, into any Phase Angle
- ◇ Remote Control Access via the Ethernet, RS-232, or IEEE-488 Communications ports
- ◇ Integrated Automatic Leveling Control to allow end-user to maintain output even with variances in temperature, or input RF level
- ◇ Standby/Enable Control
- ◇ Front Panel Display for easy viewing of System Status Locally
- ◇ Keypad buttons for full local control

CIRCUIT CONTROL (WITH FRONT PANEL CONTROLLER)

- ◇ Standby (amplifier disable)
- ◇ Gain/power setting with 20dB range
- ◇ VSWR protection Reset
- ◇ ALC On/ Off

CIRCUIT INDICATIONS (WITH FRONT PANEL CONTROLLER)

- ◇ Forward Power
- ◇ Reflected power
- ◇ VSWR Fault
- ◇ Temp Fault
- ◇ Gain Setting (VVA) percentage

CIRCUIT PROTECTIONS

- ◇ Thermal Overload
- ◇ Over Current
- ◇ Over Voltage
- ◇ Open or Short VSWR Conditions (With Front Panel Controller)

RFPA SYSTEM OPTIONS

- ◇ Switched Filter Bank
- ◇ Input Power Requirements
- ◇ Ruggedized Version
- ◇ Cabinet Requirements
- ◇ Outdoor Version
- ◇ Sample Ports
- ◇ Racking Options
- ◇ Many More!
- ◇ **Consult Factory with Specific Requirements**

